

# Cheie dinamometrica electronica

266



## Profile

---



## Caracteristicile produsului






- Atentionare atingere cuplu reglat:sonerie+12 LED
- mod de functionare:cu declansare la valoarea prestabilita
- Tipuri de unitati de masura: N-m, in-lb, ft-lb, kg-cm
- Tipul de clichet: interschimbabil
- Clichet demontabil cu 52 de dinti
- 2baterii alcaline tip AA (neincluse)
- Durata bateriei(utilizare continua):110 ore
- Durata bateriei(standby):1an

- Memoreaza pana la 250 de valori de strangere
- 9 valori de strangere prereglate
- Temperatura de lucru:-10°C ~ 60°C
- Temperatura de stocare:-20°C ~ 70°C
- Umiditate:Pana la 90% fara condens
- Test de cadere:1m
- Test de vibratii:10G
- Certificat de compatibilitate electromagnetica
- Precizie CW: +/-2%, CCW: +/-3%
- Conectare cu PC
- Download data transfer program  
([https://www.uniortools.com/res/files/assets/Uploads/266\\_calibration\\_program.zip](https://www.uniortools.com/res/files/assets/Uploads/266_calibration_program.zip))

## Warranty

- Garantie :10000 cicluri



|  |  |  |  |  |  |
|--|---|---|---|---|---|
| 627575   | 1/4"  | 1,5 - 30  | 390   | 9 x 12  | 1395  |
| 627576   | 1/2"  | 6,8 - 135   | 410   | 9 x 12  | 1619  |
| 627577   | 1/2"  | 10 - 200  | 545   | 14 x 18   | 2268  |

\* Imaginea produsului este simbolica.Toate dimensiunile sunt exprimate în mm,greutatea în grame.

0 (pictures)



Photo (pictures)



## Accessories



Cap clichet pentru 266



Cap de cheie reglabila pentru 266



Cap de cheie fixa pentru 266

## Safety tips



- Only an authorised person in a certificated service centre can perform technical maintenance.
- Tools should always be serviced and calibrated by a certified service engineer.
- Tool should only be used for precise tightening as specified in the instruction manual.
- Check instruction manual on how to read the value scale on the tool properly.
- Stop tightening after hearing a feedback from the tool.
- Use only sockets with the same square drive.
- Always return the value on the scale back to 0 after usage and before storing.



Safety (pictures)

